

(12) INTERNATIONAL APPLICATION PUBLISHED UNDER THE PATENT COOPERATION TREATY (PCT)

(19) World Intellectual Property Organization
International Bureau



(43) International Publication Date
19 July 2001 (19.07.2001)

PCT

(10) International Publication Number
WO 01/52425 A2

- (51) International Patent Classification⁷: **H04B**
- (21) International Application Number: PCT/EP01/00073
- (22) International Filing Date: 5 January 2001 (05.01.2001)
- (25) Filing Language: English
- (26) Publication Language: English
- (30) Priority Data:
09/481,948 12 January 2000 (12.01.2000) US
- (71) Applicant: **TELEFONAKTIEBOLAGET L M ERICSSON (PUBL)** [SE/SE]; S-126 25 Stockholm (SE).
- (72) Inventor: **VANGHI, Vieri**; 5370 Toscana Way #314, San Diego, CA 92122 (US).
- (74) Agents: **FÜCHSLE, Klaus et al.**; Hoffmann . Eitle, Arabellastrasse 4, 81925 Munich (DE).


- (81) Designated States (*national*): AE, AG, AL, AM, AT, AU, AZ, BA, BB, BG, BR, BY, BZ, CA, CH, CN, CR, CU, CZ, DE, DK, DM, DZ, EE, ES, FI, GB, GD, GE, GH, GM, HR, HU, ID, IL, IN, IS, JP, KE, KG, KP, KR, KZ, LC, LK, LR, LS, LT, LU, LV, MA, MD, MG, MK, MN, MW, MX, MZ, NO, NZ, PL, PT, RO, RU, SD, SE, SG, SI, SK, SL, TJ, TM, TR, TT, TZ, UA, UG, UZ, VN, YU, ZA, ZW.
- (84) Designated States (*regional*): ARIPO patent (GH, GM, KE, LS, MW, MZ, SD, SL, SZ, TZ, UG, ZW), Eurasian patent (AM, AZ, BY, KG, KZ, MD, RU, TJ, TM), European patent (AT, BE, CH, CY, DE, DK, ES, FI, FR, GB, GR, IE, IT, LU, MC, NL, PT, SE, TR), OAPI patent (BF, BJ, CF, CG, CI, CM, GA, GN, GW, ML, MR, NE, SN, TD, TG).

Published:

— without international search report and to be republished upon receipt of that report

[Continued on next page]

(54) Title: **MOBILE STATION ASSISTED FORWARD LINK OPEN LOOP POWER AND RATE CONTROL IN A CDMA SYSTEM**



(57) Abstract: In a CDMA system, forward link load measurements and mobile station channel measurements are provided to the base station controller to allow the controller to jointly select the initial traffic channel transmit power and data rate. A mobile station reports a received pilot channel signal-to-noise ratio for all base stations in sight to a base station controller. The base stations report a current forward link load estimate to the base station controller. The base station controller sets a number of traffic channel connections and a traffic channel data rate to be allocated for the traffic channel connections, and sets a target traffic channel signal-to-noise ratio based on the data rate and the number of traffic channel connections. The initial traffic channel power is computed by the controller based on estimated forward link channel characteristics, the target traffic channel received signal-to-noise ratio, the base stations' load, the number of traffic channel connections, and the traffic channel data rate.

WO 01/52425 A2



For two-letter codes and other abbreviations, refer to the "Guidance Notes on Codes and Abbreviations" appearing at the beginning of each regular issue of the PCT Gazette.

MOBILE STATION ASSISTED FORWARD LINK OPEN LOOP POWER AND RATE CONTROL IN A CDMA SYSTEM

Field of the Invention

5 The present invention relates generally to radio or wireless communications and, more particularly, relates to a method and apparatus for setting the initial transmit power and data rate in the forward link of a code division multiple access (CDMA) wireless communications system.

Background of the Invention

10 In conventional CDMA systems, forward link (base station to mobile station) transmit power and data rate control is a base station function that is activated each time one or multiple traffic connections are established. The traffic channel data rate and the traffic channel transmit power are selected such that (1) the base station forward link
15 residual capacity does not dip below a desired threshold; and (2) the desired received traffic channel signal-to-noise ratio is approximately achieved at the mobile station antenna connector. Closed loop power control is then used to adjust the traffic channel transmit power and to compensate for sub-optimum open loop estimation and changing channel conditions.

20 Conventional approaches treat traffic channel data rate and power control separately and in a heuristic fashion. With regard to power control, the initial forward link traffic channel transmit power is set to a default value at call setup and during hard handoff. If this default value is set too low, the mobile station traffic channel received signal-to-noise ratio will be insufficient to guarantee a reliable traffic channel connection,
25 which may result in a call being dropped or in service quality degradation. For this reason, the default value is usually set at a higher level than is required on average in order to provide a reliable connection even in the worst or near-worst case channel conditions.

 This approach to power control has several shortcomings. By setting the initial traffic channel transmit power to a high default level, the mobile station traffic channel
30 received signal-to-noise ratio will frequently exceed the required level and forward link capacity will be unnecessarily consumed. Moreover, a high default value increases the total transmit power peak to average ratio, leading to inefficient use of the base station

high power amplifier. Where multiple traffic channel connections must be established nearly simultaneously, and where high rate data users consume a significant amount of the total forward link capacity, the transmit power peak to average ratio increases. A reduction in the maximum average nominal transmit power may be required to avoid
5 damage to the base station high power amplifier and/or short term operation in the non-linear region of the high power amplifier, which may lead to increased spurious emission levels. Reducing the maximum average nominal transmit power, however, reduces the efficiency of the amplifier.

The transmit data rate is chosen based on the service option to be connected and on
10 the base station residual forward link (base station to mobile station) capacity. This approach to setting the data rate is also problematic. If the selected data rate is too high for a given initial traffic channel transmit power and residual forward link capacity, the mobile station may not be able to acquire the forward link traffic channel. If the traffic channel is acquired, the power allocated to the traffic channel may exceed the residual
15 forward link capacity and thereby cause overload.

Summary of the Invention

The present invention uses forward link load measurements and mobile station channel measurements to allow the base station to jointly select the initial traffic channel
20 transmit power and data rate. Using this approach, the mobile station can reliably acquire the forward link, forward link capacity consumption is minimized, base station total transmit power peak to average ratio is reduced, and the power allocated to the traffic channel is no more than the residual forward link capacity.

In one embodiment of the invention, a CDMA wireless communications system
25 that controls the initial power and data rate settings during forward link establishment of a traffic channel is provided. The system comprises a base station controller, one or more base stations that report a current forward link load estimate to the base station controller, and a mobile station that reports a received pilot channel signal-to-noise ratio to the base station controller. The base station controller sets the number of traffic channel
30 connections and the data rate to be allocated for the traffic channel connections. The base station controller also sets a target traffic channel signal-to-noise ratio based on the data rate and the number of traffic channel connections, and computes the initial traffic channel

power based on estimated forward link channel characteristics, the target traffic channel received signal-to-noise ratio, the base stations' load, the number of traffic channel connections, and the traffic channel data rate.

The present invention also provides a method for forward link open loop power and rate control in a CDMA system. The method comprises the following steps:

- (a) a mobile station reports a received pilot channel signal-to-noise ratio, $Pilot \frac{E_c}{I_o}$, for all base stations in sight to a base station controller;
- (b) the base stations report a current forward link load estimate, $\frac{Pilot E_c}{I_{or}}$, to the base station controller;
- (c) the base station controller sets a number of traffic channel connections, N , and a traffic channel data rate, R_b , to be allocated for the traffic channel connections;
- (d) the base station controller computes a target traffic channel signal-to-noise ratio, $Traffic \frac{E_b}{N_t}$, based on the data rate and the number of traffic channel connections; and
- (e) the base station controller computes the initial traffic channel transmit power relative to the pilot channel power, $\frac{Traffic P_{TX}}{Pilot P_{TX}}$, based on estimated forward link

channel characteristics, the target traffic channel received signal-to-noise ratio, the base stations' load, the number of traffic channel connections, and the traffic channel data rate.

In one implementation of this method, the base station controller computes the initial traffic channel power as:

$$\frac{Traffic P_{TX}}{Pilot P_{TX}} = \frac{Traffic \frac{E_b}{N_t}}{\frac{Pilot E_{c,i}}{I_{or,i}} \cdot Pilot \frac{E_{c,i}}{I_o} \cdot \frac{R_c}{R_b} \cdot \sum_{i=1}^N \frac{1}{Pilot E_{c,i}} - \frac{1}{n} \cdot Pilot \frac{E_{c,i}}{I_o}}$$

A method for forward link power and rate control during hard handoff in a CDMA system is also provided. The method comprises the following steps:

- (a) a mobile station searches for pilot signals on a target frequency and reports the strength of the pilot signals above a predetermined threshold to a base station controller, wherein the reported pilot signals form a requested target set;
- (b) base stations corresponding to the pilot signals in the requested target set
5 report the current total transmit pilot channel signal-to-noise ratio;
- (c) the base station controller sets a tentative granted set equal to the requested target set;
- (d) the base station controller sets a target data rate to one in use by a connected service option;
- 10 (e) the base station controller sets the required traffic channels total signal-to-noise ratio to a predefined value based on the tentative granted set and the target data rate;
- (f) the base station controller computes the required initial traffic channel power based on the tentative target set, the target data rate, the total transmit pilot channel signal-to-noise ratio and the required traffic channels total received signal-to-noise ratio;
- 15 (g) the base station controller determines whether a current base station residual capacity is above a desired threshold for the tentative granted set;
- (h) if the residual capacity is above the desired threshold, the base station controller sets a granted set equal to the tentative granted set and commands the mobile station to initiate hard handoff; and
- 20 (i) if the residual capacity is below the desired threshold, the base station controller reduces the tentative granted set and the method returns to step (f).

In another embodiment of the present invention, a method for setting the data burst transmission rate on common control channels during soft handoff is provided. The method comprises the following steps:

- 25 (a) a base station controller receives a message to be delivered to a mobile station;
- (b) the base station controller pages the mobile station on the primary common channels of a set of base stations that are serving the mobile station;
- (c) the mobile station reports its current location and the strength of pilot
30 signals above a predetermined threshold to the base station controller, wherein the reported pilot signals form a requested common control channels handoff set;

(d) the base stations corresponding to the pilot signals in the requested target set report the current total transmit pilot channel signal-to-noise ratio to the base station controller;

(e) the base station controller sets a tentative data rate equal to a maximum
5 data rate;

(f) the base station controller sets the required common control channels total signal-to-noise ratio to a predefined value based on the tentative data rate and handoff set size;

(g) the base station controller computes the required common controls channel
10 power based on the tentative data rate, the handoff set size, the total transmit pilot channel signal-to-noise ratio and the required common control channels total received signal-to-noise ratio;

(h) the base station controller determines whether a current base station residual capacity is above a desired threshold for all base stations in the handoff set;

(i) if the residual capacity is above the desired threshold, the base station
15 controller sets a granted data rate equal to the tentative data rate and transmits the message on secondary common control channels of the base station in the handoff set; and

(j) if the residual capacity is below the desired threshold, the base station controller sets the tentative data rate to the next lower supported data rate and the method
20 returns to step (g).

Objects and advantages of the present invention include any of the foregoing, taken alone or in combination. Further objects and advantages will be apparent to those of ordinary skill in the art, or will be set forth in the following disclosure.

25 Brief Description of the Drawings

The present invention is described with reference to the accompanying drawings. In the drawings, like reference numbers indicate identical or functionally similar elements, and

Figure 1 is a block diagram of a CDMA network according to the present
30 invention.

Figure 2 is a flowchart depicting a method for forward link open loop power and rate control according to the present invention.

Figure 3 is a flowchart depicting a method for power and data rate control during hard handoff according to the present invention.

Figure 4 is a flowchart depicting a method for data burst transmission rate control during soft handoff according to the present invention.

Detailed Description of Preferred Embodiments

The architecture of a basic CDMA network 100 is illustrated in **Figure 1**. A mobile station (MS) 102 communicates with one of a plurality of base stations (BS) 104...106 over a standardized air (U_m) interface. MS 102 is typically a hand-held portable unit or vehicle-installed unit containing a transceiver, an antenna and control circuitry. Many multiple stations may be in operation within network 100. Each operating mobile station represents the user-side termination of the radio path and allows the user to access network 100. Each base station 104...106 is located at the center or edge of a coverage region or cell and includes transmitter and receiver antennas mounted on a tower. Network 100 will typically contain hundreds or thousands of base stations. Hence, though only two base stations 104...106 are illustrated, it should be understood that network 100 may contain any number of base stations. Each base station represents the termination of the radio path with a mobile station on the network-side.

Base station controller (BSC) 108 manages and controls multiple base stations. The base station controller may be at the same location as a base station or may be remotely located. The base station controller communicates with base stations over a standardized A_{bis} interface. Mobile switching center (MSC) 110, in turn, coordinates the activities of all base station controllers in network 100.

The communication path from the base stations to the mobile stations is termed the forward link or downlink, while communication in the mobile station to base station direction is termed the reverse link or uplink. Each forward link CDMA signal includes a pilot channel that allow the mobile stations to make signal strength comparisons between base stations, a synchronization channel that broadcasts synchronization messages to the mobile stations, paging channels for sending control information from the base station to the mobile stations, and multiple traffic channels for transmission of voice and data information. The present invention is directed to the establishment of forward traffic channels between the base stations and mobile stations.

When a forward traffic channel is established, an initial transmit power and data rate must be set. In accordance with the present invention, base station controller 108 implements a forward link open loop power and rate control function. This function may be implemented in any suitable fashion, such as through encoding in a computer microprocessor or software. It utilizes channel measurements made by mobile station 102 and load measurements performed by multiple base stations 104...106 in order to establish traffic channel connections. The mobile station measurements include the received pilot energy to total interference power spectral density ratio of all detected base stations 104...106 that are candidates for traffic channel connection establishment. The base station load measurements include the transmit pilot energy to total power spectral density ratio of each of the base stations 104...106 suggested by mobile station 102 as a candidate for traffic channel establishment.

Figure 2 illustrates in general form a method 120 for forward link open loop power and rate control. When base station controller 108 decides that new traffic channel connections should be established, such as during call setup or hard handoff, it requests mobile station 102 to report the received pilot channel signal-to-noise ratio of all base stations 104...106 in sight (step 122). Alternatively, mobile station 102 may autonomously report such measurements. Base station controller 108 interrogates base stations 104...106 for the current forward link load estimate (step 124). The admission control function of base station controller 108 decides upon the number of traffic channel connections and the data rate to be allocated for the traffic channel connections (step 126). The target received traffic channel signal-to-noise ratio is selected on the basis of the data rate and the number of connections in soft handoff (step 128). Base station controller 108 computes the required traffic channel power based on the estimated forward link channel characteristics, the target traffic channel received signal-to-noise ratio, the base stations' load, the number of traffic channel connections, and the traffic channel data rate (step 130). The traffic channel power calculated in this manner is used as the initial traffic channel transmit power by all base stations 104...106 that are to establish the traffic channel connection with mobile station 102.

More particularly, the optimum initial traffic channel transmit power is computed as follows. Base station controller 108 assumes that each forward link channel has n equal strength paths. The received i th pilot chip energy to total power spectral density ratio

(reported by the mobile stations in step 122), and the received i th traffic channel bit energy to effective noise power spectral density ratio (set by the base station controller in step 126) are, respectively:

$$Pilot \frac{E_{c,i}}{I_o} = \frac{\frac{Pilot E_{c,i}}{I_{or,i}}}{\frac{\hat{I}_{oc}}{\hat{I}_{or,i}} + \sum_{j=1, j \neq i}^N \frac{\hat{I}_{or,j}}{\hat{I}_{or,i}} + 1}, \text{ for } i=1 \dots N \text{ (equation 1); and}$$

5

$$Traffic \frac{E_{b,i}}{N_i} = \frac{\frac{Traffic E_{b,i}}{I_{or,i}}}{\frac{\hat{I}_{oc}}{\hat{I}_{or,i}} + \sum_{j=1, j \neq i}^N \frac{\hat{I}_{or,j}}{\hat{I}_{or,i}} + \frac{n-1}{n}}, \text{ for } i=1 \dots N \text{ (equation 2).}$$

That is:

$$10 \quad Traffic \frac{E_{b,i}}{N_i} = \frac{\frac{Traffic P_{Tx}}{Pilot P_{Tx}} \cdot \frac{R_c}{R_b} \cdot \frac{Pilot E_{c,i}}{I_{or,i}}}{\frac{Pilot E_{c,i}}{I_{or,i}} - \frac{1}{n}} = \frac{\frac{Traffic P_{Tx}}{Pilot P_{Tx}} \cdot \frac{R_c}{R_b} \cdot \frac{Pilot E_{c,i}}{I_{or,i}} \cdot Pilot \frac{E_{c,i}}{I_o}}{\frac{Pilot E_{c,i}}{I_{or,i}} - \frac{1}{n} \cdot Pilot \frac{E_{c,i}}{I_o}} \quad \text{(equation)}$$

3).

The total received traffic channel bit energy to effective noise power spectral density ratio, then, is:

$$15 \quad Traffic \frac{E_b}{N_i} = \frac{Traffic P_{Tx}}{Pilot P_{Tx}} \cdot \frac{R_c}{R_b} \cdot \sum_{i=1}^N \frac{\frac{Pilot E_{c,i}}{I_{or,i}} \cdot Pilot \frac{E_{c,i}}{I_o}}{\frac{Pilot E_{c,i}}{I_{or,i}} - \frac{1}{n} \cdot Pilot \frac{E_{c,i}}{I_o}} \quad \text{(equation 4).}$$

Base station controller 108 can solve for the optimum open loop estimate, that is, the initial value of the traffic channel transmit power (step 130), relative to the pilot transmit power:

$$\frac{TrafficP_{Tx}}{PilotP_{Tx}} = \frac{Traffic \frac{E_b}{N_t}}{\frac{PilotE_{c,i}}{I_{or,i}} \cdot Pilot \frac{E_{c,i}}{I_o}} \quad (\text{equation 5}).$$

$$\frac{R_c}{R_b} \cdot \sum_{i=1}^N \frac{1}{\frac{PilotE_{c,i}}{I_{or,i}} - \frac{1}{n} \cdot Pilot \frac{E_{c,i}}{I_o}}$$

The transmit pilot energy to total power spectral density ratio, $\frac{PilotE_c}{I_{or}}$, is reported by each base station 104...106 to base station controller 108. The target base stations received pilot energy to total interference power spectral density ratio, $Pilot \frac{E_c}{I_o}$, are measured by mobile station 102 and reported to the base station by means of signaling. The base station computes the initial traffic channel power, relative to the pilot channel transmit power, $\frac{TrafficP_{Tx}}{PilotP_{Tx}}$, for the desired target $Traffic \frac{E_b}{N_t}$ and the desired traffic channel data rate, using the formulas above.

If the required traffic channel power is such that the residual forward link capacity would decrease below the desired minimum level, the base station may decide to decrease the selected traffic channel data rate and re-compute the required traffic channel transmit power. As an example, the formula above in the case of $N=n=1$ simplifies to:

$$\frac{TrafficP_{Tx}}{PilotP_{Tx}} = \frac{Traffic \frac{E_b}{N_t} \cdot \left(\frac{PilotE_c}{I_{or}} - Pilot \frac{E_c}{I_o} \right)}{\frac{R_c}{R_b} \cdot \frac{PilotE_c}{I_{or}} \cdot Pilot \frac{E_c}{I_o}} \quad (\text{equation 6}).$$

The present invention is applicable to call setup, both in the cases of channel assignment in soft handoff or not, and inter-frequency hard handoff in TIA/EIA-95B compliant systems. In such systems, the $Pilot \frac{E_c}{I_o}$ measurement reported by mobile station 102 is reported to the base station by means of the ACTIVE_PILOT_STRENGTH and PILOT_STRENGTH fields of the *Origination Message*, *Page Response Message*, and *Candidate Frequency Report Message*. The present invention is also applicable to IS-2000 systems to select the initial transmit power and data rate of the forward link common control channels, both when operated in soft handoff or not.

Figure 3 illustrates a method 140 implementing the procedures described above for setting the initial transmit power and data rate in a hard handoff situation. Hard handoff may be necessary when two base stations are not synchronized or are using different frequency bands. In step 142, the mobile station periodically searches for pilot signals on the target frequency and reports the strength of the pilot signals that are above a predetermined threshold to base station controller 108. These reported pilot signals form the requested target set of base stations. At decision node 144, base station controller 108 determines whether a handoff is necessary. If handoff is not necessary, the method returns to step 142. If handoff is necessary, base station controller 108 queries each base station 104...106 corresponding to the pilot signals in the requested set for the current transmit pilot channel energy to total power spectral density ratio, $\frac{Pilot E_c}{I_{or}}$ (step 146).

Next, base station controller 108 sets the tentative granted set (the number of traffic channel connections) equal to the requested target set (step 148) and sets the target data rate equal to the one in use by the connected service option (step 150). In step 152, base station controller 108 sets the required target traffic channels total received signal-to-noise ratio, $Traffic \frac{E_b}{N_t}$, to a predefined value corresponding to the data rate of the connected voice service option and tentative target set size (number of traffic channel connections). The current total received $Traffic \frac{E_b}{N_t}$ of the source active set, which is known to base station controller 108, may also be used to estimate the required $Traffic \frac{E_b}{N_t}$ of the target active set.

In step 154, base station controller 108 computes the required initial traffic channel power for the tentative target set, target data rate, total pilot channel transmit energy to total power spectral density ratio $\frac{Pilot E_c}{I_{or}}$, and the required traffic channel total received signal-to-noise ratio $Traffic \frac{E_b}{N_t}$, in accordance with the formulae set forth above (initial power computed using equation 5). Next, base station controller 108 determines whether the current base station residual capacity, adjusted to consider the additional links to be set

up each with power allocation as computed above, is above the desired threshold for all of the base stations in the tentative target set (decision node 156). If the residual capacity is above this desired threshold for the tentative target set, base station controller sets the granted set equal to the tentative granted set (step 158) and commands mobile station 102 to initiate hard handoff to the granted target set (step 160). If the residual capacity is below the desired threshold for the tentative target set, base station controller 108 prunes the tentative granted set (number of traffic channel connections) (step 162), and then repeats the computations in step 154.

Figure 4 illustrates a method 170 implementing the procedures described above for setting the data burst transmission rate on common control channels in a soft handoff situation. In step 172, the base station controller receives a message to be delivered to the mobile station. The base station controller pages the mobile station, in step 174, on the primary common channels of a set of base stations that presumably are serving the mobile station. In step 176, the mobile station responds informing the base station controller of its current location and of the strength of the pilot signals that are detected above a predetermined threshold. These reported pilot signals form the requested common control channels handoff set (step 178). Next, base station controller 108 queries each base station 104...106 corresponding to a pilot signal in the requested handoff set for the current pilot channel transmit energy to total power spectral density ratio, $\frac{PilotE_c}{I_{or}}$ (step 180).

In step 182, base station controller 108 sets the tentative data rate equal to the maximum data rate and, in step 184, sets the required common controls channel total received signal-to-noise ratio, $\frac{E_b}{N_t}$, to a predefined value corresponding to the tentative data rate and handoff set size. The base station controller then computes the required common controls channel power for the tentative data rate, handoff set, pilot channel transmit energy to total power spectral density ratio $\frac{PilotE_c}{I_{or}}$, and the required common controls channel total received signal-to-noise ratio $\frac{E_b}{N_t}$, in accordance with the formulae set forth above (step 186).

Next, base station controller 108 determines whether the current base station residual capacity, adjusted to consider the additional links to be set up each with power allocation as computed above, is above the desired threshold for all of the base stations in the handoff set (decision node 188). If the residual capacity is above this desired threshold for the tentative handoff set, base station controller sets the granted data rate equal to the tentative data rate (step 190) and transmits the message on the secondary common control channels of the base station in the handoff set (step 192). If the residual capacity is below the desired threshold for one or more of the base stations in the handoff set, base station controller 108 sets the tentative data rate to the next lower supported data rate (step 162), and then repeats the computations in step 186.

While various embodiments of the present invention have been described above, it should be understood that these embodiments have been presented by way of example only, and not limitation. The breadth and scope of the present invention is not limited to any of the described embodiments, but rather, is defined in accordance with the following claims and their equivalents.

Claims

1. A CDMA wireless communications system that controls the initial power and data rate settings during forward link establishment of a traffic channel comprising:

a base station controller;

5 one or more base stations that report a current forward link load estimate to the base station controller; and

a mobile station that reports a received pilot channel signal-to-noise ratio to the base station controller,

wherein the base station controller sets the number of traffic channel connections
10 and the data rate to be allocated for the traffic channel connections, computes a target traffic channel signal-to-noise ratio based on the data rate and the number of traffic channel connections, and computes the initial traffic channel power based on estimated forward link channel characteristics, the target traffic channel received signal-to-noise ratio, the base stations' load, the number of traffic channel connections, and the traffic
15 channel data rate.

2. In a CDMA wireless communications system having a base station controller, one or more base stations, and a mobile station, a method for forward link open loop power and rate control comprising the following steps:

20 (a) the mobile station reports a received pilot channel signal-to-noise ratio for all base stations in sight to the base station controller;

(b) the base stations report a current forward link load estimate to the base station controller;

(c) the base station controller sets a number of traffic channel connections and
25 a traffic channel data rate to be allocated for the traffic channel connections;

(d) the base station controller computes a target traffic channel signal-to-noise ratio based on the data rate and the number of traffic channel connections; and

(e) the base station controller computes the initial traffic channel power based on estimated forward link channel characteristics, the target traffic channel received
30 signal-to-noise ratio, the base stations' load, the number of traffic channel connections, and the traffic channel data rate.

3. A method as claimed in claim 2, wherein in step (a), the base station controller first requests the mobile station to report the received pilot channel signal-to-noise ratio.

5 4. A method as claimed in claim 2, wherein in step (a), the mobile station autonomously reports the received pilot channel signal-to-noise ratio to the base station controller.

5. A method as claimed in claim 2, wherein in step (b), the base station controller interrogates the base stations for the current forward link load estimate.

6. A method as claimed in claim 2, wherein in step (e), the base station controller computes the initial traffic channel power as:

$$\frac{TrafficP_{Tx}}{PilotP_{Tx}} = \frac{Traffic \frac{E_b}{N_t}}{\frac{R_c}{R_b} \cdot \sum_{i=1}^N \frac{\frac{PilotE_{c,i}}{I_{or,i}} \cdot Pilot \frac{E_{c,i}}{I_o}}{\frac{PilotE_{c,i}}{I_{or,i}} - \frac{1}{n} \cdot Pilot \frac{E_{c,i}}{I_o}}}$$

15

7. In a CDMA wireless communications system having a base station controller, one or more base stations, and a mobile station, a method for forward link power and rate control during hard handoff comprising the following steps:

- (a) the mobile station searches for pilot signals on a target frequency and reports the strength of the pilot signals above a predetermined threshold to the base station controller, wherein the reported pilot signals form a requested target set;
- (b) the base stations corresponding to the pilot signals in the requested target set report the current total transmit pilot channel signal-to-noise ratio;
- (c) the base station controller sets a tentative granted set equal to the requested target set;
- (d) the base station controller sets a target data rate to one in use by a connected service option;

- (e) the base station controller sets the required traffic channels total signal-to-noise ratio to a predefined value based on the tentative granted set and the target data rate;
- (f) the base station controller computes the required initial traffic channel power based on the tentative target set, the target data rate, the total transmit pilot channel signal-to-noise ratio and the required traffic channels total received signal-to-noise ratio;
- (g) the base station controller determines whether a current base station residual capacity is above a desired threshold for the tentative granted set;
- (h) if the residual capacity is above the desired threshold, the base station controller sets a granted set equal to the tentative granted set and commands the mobile station to initiate hard handoff; and
- (i) if the residual capacity is below the desired threshold, the base station controller reduces the tentative granted set and the method returns to step (f).

8. A method as claimed in claim 7, wherein in step (b), the base station controller queries each base station for the current total transmit pilot channel signal-to-noise ratio.

9. A method as claimed in claim 7, wherein in step (f), the initial traffic channel power is computed as:

$$\frac{TrafficP_{Tx}}{PilotP_{Tx}} = \frac{Traffic \frac{E_b}{N_t}}{\frac{R_c}{R_b} \cdot \sum_{i=1}^N \frac{\frac{PilotE_{c,i}}{I_{or,i}} \cdot Pilot \frac{E_{c,i}}{I_o}}{\frac{PilotE_{c,i}}{I_{or,i}} - \frac{1}{n} \cdot Pilot \frac{E_{c,i}}{I_o}}}$$

10. In a CDMA wireless communications system having a base station controller, one or more base stations, and a mobile station, a method for setting the data burst transmission rate on common control channels during soft handoff comprising the following steps:

- (a) the base station controller receives a message to be delivered to the mobile station;

(b) the base station controller pages the mobile station on the primary common channels of a set of base stations that are serving the mobile station;

(c) the mobile station reports its current location and the strength of pilot signals above a predetermined threshold to the base station controller, wherein the reported pilot signals form a requested common control channels handoff set;

(d) the base stations corresponding to the pilot signals in the requested target set report the current total transmit pilot channel signal-to-noise ratio to the base station controller;

(e) the base station controller sets a tentative data rate equal to a maximum data rate;

(f) the base station controller sets the required common control channels total signal-to-noise ratio to a predefined value based on the tentative data rate and handoff set size;

(g) the base station controller computes the required common controls channel power based on the tentative data rate, the handoff set, the total transmit pilot channel signal-to-noise ratio and the required common control channels total received signal-to-noise ratio;

(h) the base station controller determines whether a current base station residual capacity is above a desired threshold for all base stations in the handoff set;

(i) if the residual capacity is above the desired threshold, the base station controller sets a granted data rate equal to the tentative data rate and transmits the message on secondary common control channels of the base station in the handoff set; and


(j) if the residual capacity is below the desired threshold, the base station controller sets the tentative data rate to the next lower supported data rate and the method returns to step (g).

11. A method as claimed in claim 10, wherein in step (d), the base station controller queries each base station for the current total transmit pilot channel signal-to-noise ratio.


12. A method as claimed in claim 10, wherein in step (g), the initial traffic channel power is computed as:

$$\frac{\text{Traffic} P_{Tx}}{\text{Pilot} P_{Tx}} = \frac{\text{Traffic} \frac{E_b}{N_t}}{\frac{\text{Pilot} E_{c,i}}{I_{or,i}} \cdot \text{Pilot} \frac{E_{c,i}}{I_o}} \cdot \frac{R_c}{R_b} \cdot \sum_{i=1}^N \frac{I_{or,i}}{\frac{\text{Pilot} E_{c,i}}{I_{or,i}} - \frac{1}{n} \cdot \text{Pilot} \frac{E_{c,i}}{I_o}}$$


1/4

**Figure 1**


2/4

**Figure 2**

3/4

**Figure 3**

4 / 4

**Figure 4**

THIS PAGE BLANK (USPTO)

(12) INTERNATIONAL APPLICATION PUBLISHED UNDER THE PATENT COOPERATION TREATY (PCT)

(19) World Intellectual Property Organization
International Bureau



(43) International Publication Date
19 July 2001 (19.07.2001)

PCT

(10) International Publication Number
WO 01/52425 A3

- (51) International Patent Classification⁷: **H04B 7/005**
- (21) International Application Number: PCT/EP01/00073
- (22) International Filing Date: 5 January 2001 (05.01.2001)
- (25) Filing Language: English
- (26) Publication Language: English
- (30) Priority Data:
09/481,948 12 January 2000 (12.01.2000) US
- (71) Applicant: **TELEFONAKTIEBOLAGET L M ERICSSON (PUBL)** [SE/SE]; S-126 25 Stockholm (SE).
- (72) Inventor: **VANGHI, Vieri**; 5370 Toscana Way #314, San Diego, CA 92122 (US).
- (74) Agents: **FÜCHSLE, Klaus** et al.; Hoffmann, Eitle, Arabellastrasse 4, 81925 Munich (DE).


- (81) Designated States (*national*): AE, AG, AL, AM, AT, AU, AZ, BA, BB, BG, BR, BY, BZ, CA, CH, CN, CR, CU, CZ, DE, DK, DM, DZ, EE, ES, FI, GB, GD, GE, GH, GM, HR, HU, ID, IL, IN, IS, JP, KE, KG, KP, KR, KZ, LC, LK, LR, LS, LT, LU, LV, MA, MD, MG, MK, MN, MW, MX, MZ, NO, NZ, PL, PT, RO, RU, SD, SE, SG, SI, SK, SL, TJ, TM, TR, TT, TZ, UA, UG, UZ, VN, YU, ZA, ZW.
- (84) Designated States (*regional*): ARIPO patent (GH, GM, KE, LS, MW, MZ, SD, SL, SZ, TZ, UG, ZW), Eurasian patent (AM, AZ, BY, KG, KZ, MD, RU, TJ, TM), European patent (AT, BE, CH, CY, DE, DK, ES, FI, FR, GB, GR, IE, IT, LU, MC, NL, PT, SE, TR), OAPI patent (BF, BJ, CF, CG, CI, CM, GA, GN, GW, ML, MR, NE, SN, TD, TG).

Published:
— with international search report

(88) Date of publication of the international search report:
16 May 2002

[Continued on next page]

(54) Title: MOBILE STATION ASSISTED FORWARD LINK TRANSMISSION POWER AND DATA RATE CONTROL IN A CDMA SYSTEM



(57) Abstract: In a CDMA system, forward link load measurements and mobile station channel measurements are provided to the base station controller to allow the controller to jointly select the initial traffic channel transmit power and data rate. A mobile station (102) reports a received pilot channel signal-to-noise ratio for all base stations (104, 106) in sight to a base station controller (108). The base stations report a current forward link load estimate to the base station controller. The base station controller sets a number of traffic channel connections and a traffic channel data rate to be allocated for the traffic channel connections, and sets a target traffic channel signal-to-noise ratio based on the data rate and the number of traffic channel connections. The initial traffic channel power is computed by the controller based on estimated forward link channel characteristics, the target traffic channel received signal-to-noise ratio, the base stations' load, the number of traffic channel connections, and the traffic channel data rate.

WO 01/52425 A3



For two-letter codes and other abbreviations, refer to the "Guidance Notes on Codes and Abbreviations" appearing at the beginning of each regular issue of the PCT Gazette.

INTERNATIONAL SEARCH REPORT

International Application No

PC1/EP 01/00073

A. CLASSIFICATION OF SUBJECT MATTER
IPC 7 H04B7/005

According to International Patent Classification (IPC) or to both national classification and IPC

B. FIELDS SEARCHED

Minimum documentation searched (classification system followed by classification symbols)

IPC 7 H04B H04Q

Documentation searched other than minimum documentation to the extent that such documents are included in the fields searched

Electronic data base consulted during the international search (name of data base and, where practical, search terms used)

EPO-Internal

C. DOCUMENTS CONSIDERED TO BE RELEVANT

Category *	Citation of document, with indication, where appropriate, of the relevant passages	Relevant to claim No.
A	WO 99 55112 A (HIRAMATSU KATSUHIKO ;UE TOYOKI (JP); KATO OSAMU (JP); MATSUSHITA E) 28 October 1999 (1999-10-28) -& EP 0 986 282 A (MATSUSHITA ELECTRIC INDUSTRIAL CO) 15 March 2000 (2000-03-15) column 1, last line -column 2, line 5 column 7, line 30 -column 8, line 42; figures 1,2,11-13 column 16, line 24 - line 53; figures 28,29 column 17, line 11 -column 18, line 10 ---	1-5,7,8, 10,11
A	US 5 771 451 A (TAKAI KENICHI ET AL) 23 June 1998 (1998-06-23) abstract; figures 1,4-11 column 2, line 52 - line 58 column 6, line 16 -column 7, line 23 --- -/--	1,2,6,7, 9,10,12



Further documents are listed in the continuation of box C



Patent family members are listed in annex.

* Special categories of cited documents:

- *A* document defining the general state of the art which is not considered to be of particular relevance
- *E* earlier document but published on or after the international filing date
- *L* document which may throw doubts on priority claim(s) or which is cited to establish the publication date of another citation or other special reason (as specified)
- *O* document referring to an oral disclosure, use, exhibition or other means
- *P* document published prior to the international filing date but later than the priority date claimed

T later document published after the international filing date or priority date and not in conflict with the application but cited to understand the principle or theory underlying the invention

X document of particular relevance; the claimed invention cannot be considered novel or cannot be considered to involve an inventive step when the document is taken alone

Y document of particular relevance; the claimed invention cannot be considered to involve an inventive step when the document is combined with one or more other such documents, such combination being obvious to a person skilled in the art.

& document member of the same patent family

Date of the actual completion of the international search

9 January 2002

Date of mailing of the international search report

16/01/2002

Name and mailing address of the ISA

European Patent Office, P.B. 5818 Patentlaan 2
NL - 2280 HV Rijswijk
Tel. (+31-70) 340-2040, Tx. 31 651 epo nl.
Fax: (+31-70) 340-3016

Authorized officer

Sieben, S

INTERNATIONAL SEARCH REPORT

International Application No

PC1/EP 01/00073

C.(Continuation) DOCUMENTS CONSIDERED TO BE RELEVANT

Category *	Citation of document, with indication, where appropriate, of the relevant passages	Relevant to claim No.
A	<p>EP 0 767 548 A (AT & T CORP) 9 April 1997 (1997-04-09)</p> <p>abstract column 1, line 53 -column 2, line 37 column 8, line 24 - line 34 column 10, line 31 -column 11, line 3; figure 6 column 13, line 14 -column 14, line 24; figures 1,5,8</p> <p>---</p>	<p>1,2,4,5, 7,8,10, 11</p>
A	<p>US 5 884 187 A (TIEDEMANN JR EDWARD G ET AL) 16 March 1999 (1999-03-16) abstract; figure 6 column 12, line 65 -column 13, line 20 column 14, line 18 - line 59; figure 4 column 17, line 35 -column 18, line 11 column 20, line 42 - line 64</p> <p>-----</p>	<p>1-5,7,8, 10,11</p>

INTERNATIONAL SEARCH REPORT

Information on patent family members

International Application No

PCT/EP 01/00073

Patent document cited in search report		Publication date	Patent family member(s)	Publication date
WO 9955112	A	28-10-1999	AU 3171999 A	08-11-1999
			BR 9906339 A	19-09-2000
			CN 1263681 T	16-08-2000
			EP 1122965 A1	08-08-2001
			EP 0986282 A1	15-03-2000
			WO 9955112 A1	28-10-1999
			JP 2000049663 A	18-02-2000
US 5771451	A	23-06-1998	JP 2762965 B2	11-06-1998
			JP 9074378 A	18-03-1997
EP 0767548	A	09-04-1997	US 5734646 A	31-03-1998
			CA 2184772 A1	06-04-1997
			EP 0767548 A2	09-04-1997
			JP 3066327 B2	17-07-2000
			JP 9186646 A	15-07-1997
			NO 964220 A	07-04-1997
			US 6088335 A	11-07-2000
			US 6069883 A	30-05-2000
US 5884187	A	16-03-1999	AU 2323497 A	01-10-1997
			BR 9708430 A	03-08-1999
			CA 2248833 A1	18-09-1997
			CN 1218602 A	02-06-1999
			EP 0886985 A1	30-12-1998
			JP 2000509213 T	18-07-2000
			TW 424367 B	01-03-2001
			WO 9734439 A1	18-09-1997

THIS PAGE BLANK (USPTO)